

## Light5 E-Bike light compability list

Manufacturer and model	Output (V, A / W)	Compatible with EB1000	Compatible with EB2000
<b>Bosch</b>			
Performance Line CX (gen4)	12V, 1.5A / <b>17W</b>	X	X
Performance Line CX (gen3)	12V, 1.5A / <b>17W</b>	X	X
Performance Line CX	12V, 1.5A / <b>17W</b>	X	X
Performance Line	6V, 1.5A / <b>9W</b>	X	
Active Line Plus	12V, 1.5A / <b>17W</b>	X	X
Active Line	12V, 1.5A / <b>17W</b>	X	X
Smart System (2022, gen4)	12V, 1.5A / <b>17W</b>	X	X
<b>Shimano</b>			
EP8	12V, 2A / <b>24W</b>	X	X
E8000	6V, 2A / <b>12W</b>	X	
E7000	12V, 2A / <b>24W</b>	X	X
E6100	12V, 2A / <b>24W</b>	X	X
E5000	12V, 2A / <b>24W</b>	X	X
<b>Yamaha</b>			
PW-X	6V, 1.5A / <b>9W</b>	X	
PW-TE	6V, 1.5A / <b>9W</b>	X	
PW-ST	6V, 1.5A / <b>9W</b>	X	
PW-CE	6V, 1.5A / <b>9W</b>	X	
PW-X2	6V, 1.5A / <b>9W</b>	X	
PW-X87	6V, 4A / <b>24W</b>	X	X
PW-SE	6V, 1A / <b>6W</b>		
<b>Brose</b>			
Drive S (Mag)	12V, 2A / <b>24W</b>	X	X
Drive S	6V, 2.5A / <b>14W</b>	X	
Drive T	6V, 1.2A / <b>7W</b>	X	
Drive TF	6V, 1.2A / <b>7W</b>	X	
Drive C	6V, 1.2A / <b>7W</b>	X	
Gen1	6V, 1.2A / <b>7W</b>	X	
<b>Specialized (Brose)</b>			
1.1 SL	12V, 0.7A / <b>8W</b>	X	
1.3	6V, 2.5A / <b>14W</b>	X	
2.1	12V, 2A / <b>24W</b>	X	X
2.2	12V, 2A / <b>24W</b>	X	X
<b>Bafang</b>			
MM G522.250.C	12V, 0.5A / <b>6W</b>	X	
MM G333.250.C	12V, 0.5A / <b>6W</b>	X	
All other models	6V, 0.5A / <b>3W</b>		

<b>BionX</b>	12V, 2A / <b>24W</b>	<b>X</b>	<b>X</b>
<b>Neodrives</b>			
UR-V10	12V, 3A / <b>36W</b>	<b>X</b>	<b>X</b>
UR-V8	12W, 1.5A / <b>18W</b>	<b>X</b>	
Integrale	12W, 1.5A / <b>18W</b>	<b>X</b>	
ZEG MY20	12W, 1.5A / <b>18W</b>	<b>X</b>	
<b>Continental</b>			
Prime	6V/ 2A / <b>12W</b>	<b>X</b>	
Revolution	6V/ 2A / <b>12W</b>	<b>X</b>	
<b>Panasonic</b>			
GXO	13.5V, 1.5A / <b>20W</b>	<b>X</b>	<b>X</b>